

Version 2.06 projects and RADAR 24 / RADAR II compatibility

RADAR 24 and RADAR II drives can be interchanged freely using the standard Kingston DE-100 drive carriers, the only exception being projects that are stored in the 2.06 (or earlier) format.

You can transfer projects recorded in earlier versions of software to RADAR units running later versions of software by translating the project files into a version independent format.

The procedure for upgrading the projects is as follows:

- 1) To prepare your 2.06 (and pre-2.06) disk(s) for transfer, choose "UPGRADE SYSTEM" from the SYSTEM menu and answer "YES".
- 2) When you press the enter key, RADAR will save all the projects on the audio drive in a version-independent (upgrade) format. This operation will take a few seconds per project.
- 3) When it is complete, the message: TURN OFF POWER & BOOT UPGRADE S/W will appear.
- 4) If you have another audio drive, swap it into the drive bay, reboot RADAR, and repeat the above steps.
- 5) Continue until all audio drives have been put into upgrade mode.

Now when the upgraded disk is mounted on a RADAR 24 or RADAR II with a later version of the operating system the projects will be converted into the new format.